

## Residual current circuit breaker (RCCB), 40A, 4 p, 300mA, type AC

Powering Business Worldwide\*

Part no. PF7-40/4/03-DE Article no. 263588

Similar to illustration

	livery		 -	· • • • • • • • • • • • • • • • • • • •	2 122	•
	IIVEIV	, ,		7		-

Basic function			Residual current circuit breakers
Dasic function			Hesidual Cult Cit Cult Di Eakers
Number of poles			4 pole
Application			Switchgear for residential and commercial applications
Rated current	In	Α	40
Rated short-circuit strength	I <sub>cn</sub>	kA	10
Rated fault current	$I_{\Delta N}$	Α	0.3
Туре			Type AC
Tripping		Α	non-delayed
Product range			PF7
Sensitivity			AC current sensitive
Impulse withstand current			Partly surge-proof 250 A

## **Design verification as per IEC/EN 61439**

In	Α	40
P <sub>vid</sub>	W	0
P <sub>vid</sub>	W	8.4
P <sub>vs</sub>	W	0
P <sub>diss</sub>	W	0
	°C	-25
	°C	55
		Starting at 40 °C, the max. permissible continuous current decreases by 3% for every 1 °C
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Does not apply, since the entire switchgear needs to be evaluated.
		Does not apply, since the entire switchgear needs to be evaluated.
		Meets the product standard's requirements.
		Does not apply, since the entire switchgear needs to be evaluated.
		Meets the product standard's requirements.
		Does not apply, since the entire switchgear needs to be evaluated.
		Does not apply, since the entire switchgear needs to be evaluated.
		Is the panel builder's responsibility.
		Is the panel builder's responsibility.
		Is the panel builder's responsibility.
		Is the panel builder's responsibility.
		Is the panel builder's responsibility.
		The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
		Is the panel builder's responsibility. The specifications for the switchgear must be observed.
	P <sub>vid</sub> P <sub>vid</sub> P <sub>vs</sub>	P <sub>vid</sub> W P <sub>vid</sub> W P <sub>vs</sub> W P <sub>diss</sub> W °C

10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

## **Technical data ETIM 6.0**

Circuit breakers and fuses (EG000020) / Residual current circuit breaker (RCCB) (EC000003)

Electric engineering, automation, process control engineering / Electrical installation, device / Residual current protection system / Residual current circuit breaker (RCCB)

voltage V current A rent A nod nt type	A 40 A 0.3
current A rrent A nod	A 40 A 0.3
rent A nod Intype	A 0.3
nod Int type	
nt type	
	DIN rail
action	AC
scholl	No
reaking capacity (Icw) kA	kA 10
capacity kA	kA 0.25
	50 Hz
ipment possible	Yes
ection (IP)	IP20
ize (in accordance with DIN 43880)	1
er of modular spacings	4
mm	mm 69.5
ayed tripping	